High Frequency 200mA Charge Pump Inverter or Doubler

FEATURES

- Inverts or Doubles Input Supply Voltage
- 92% Power Efficiency at 100mA
- 120kHz/900kHz Selectable Oscillator Frequency
- 4.5Ω Output Resistance Using 3.3μF Ceramic Caps
- Low Voltage Battery Operation
- Ideal for 3.6V Lithium Ion Battery or 5.0V Input
- High Output Current – 200mA
- Low Profile Solution
- 1.5V Inverter Startup Guaranteed



Now Available in Lead Free Packaging

- Pin-Compatible High-Current Upgrade of the ICL7660 and 660 Industry Standard
- Smallest Package Available for the 660 Industry Standard – 8 pin MSOP

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

DESCRIPTION

The **SP6661** is a CMOS DC-DC Monolithic Voltage Converter that can be implemented as a Voltage Inverter or a Positive Voltage Doubler. As a Voltage Inverter, a -1.5V to -5.0V output can be converted from a +1.5V to +5.0V input. As a Voltage Doubler, a +5.0V to +10.0V output can be provided from a +2.5V to +5.0V input. The **SP6661** is ideal for both battery-powered and board level voltage conversion applications with a typical operating current of 3mA and a high efficiency (>90%) over most of its load-current range. Typical end products for this device are disk drive supplies, operational amplifier and interface power supplies, medical instruments, and hand held and laptop computers. The **SP6661** is available in 8-pin NSOIC, and μSOIC packages.

TYPICAL APPLICATIONS CIRICUIT




Figure 1: Voltage Inverter




Figure 2: Voltage Doubler

 © Copyright 2004 Sipex Corporation

ABSOLUTE MAXIMUM RATINGS

These are stress ratings only and functional operation of the device at these ratings or any other above those indicated in the operation sections of the specifications below is not implied. Exposure to absolute maximum rating conditions for extended periods of time may affect reliability.

Power Supply Voltage
(V+ to GND or GND to OUT).....+5.6V
LV Input Voltages.....(OUT - 0.3V) to (V+ + 0.3V)
FC and OSC Input Voltages.....The least negative of (OUT - 0.3V) or (V+ - 5.6V) to (V+ + 0.3V)
OUT and V+ Continuous Output Current.....200mA
Output Short-Circuit Duration to GND (Note 1).....1s
Operating Temperature Ranges
SP6661E_.....-40˚C to +85˚C
Continuous Power Dissipation (T_{AMB} = 70˚C)
NSOIC (derate 5.88mW/˚C above +70˚C).....471mW
µSOIC (derate 4.10mW/˚C above +70˚C).....330mW
Operating Temperature.....-40˚C to +85˚C
Storage Temperature.....-65˚C to +150˚C
Lead Temperature (soldering 10s).....+300˚C

ELECTRICAL CHARACTERISTICS

PARAMETER	MIN.	TYP.	MAX.	UNITS	CONDITIONS
Inverter Circuit at Low Frequency with 22µF Capacitors					
V+ = +5.0V, C1 = C2 = C3 = 22µF, FC = open, LV = GND, T_{AMB} = T_{MIN} to T_{MAX}; refer to *Figure 1* test circuit. Note 2					
Supply Voltage Range	1.5		5.3	V	R_L = 500Ω
Start-Up Voltage		0.93		V	
Supply Current		3	6	mA	No Load
Max Output Current	200			mA	
Oscillator Input Current		±1		µA	
Oscillator Frequency	70	120	170	kHz	
Output Resistance		5	7	Ω	I_L = 100mA, Note 3
Voltage Conversion Efficiency	99.0	99.9		%	No Load
Power Efficiency	80 70	89 82		%	I_L = 100mA I_L = 200mA
Doubler Circuit at Low Frequency with 22µF Capacitors					
V+ = +5.0V, C1 = C2 = C3 = 22µF, FC = open, LV = GND, T_{AMB} = T_{MIN} to T_{MAX}; refer to *Figure 22* test circuit. Note 2					
Supply Voltage Range	2.5		5.3	V	R_L = 1kΩ
Start-Up Voltage		1.5		V	
Supply Current		3	6	mA	No Load
Max Output Current	200			mA	
Oscillator Input Current		±1		µA	
Oscillator Frequency	70	120	170	kHz	
Output Resistance		4.5	7	Ω	I_L = 100mA, Note 3
Voltage Conversion Efficiency	99.0	99.9		%	No Load
Power Efficiency	89 79	94 90		%	I_L = 100mA I_L = 200mA

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

 © Copyright 2004 Sipex Corporation

PARAMETER	MIN.	TYP.	MAX.	UNITS	CONDITIONS
Inverter Circuit at High Frequency with 3.3µF Capacitors					
V+ = +5.0V, C1 = C2 = C3 = 3.3µF, FC = V+, LV = GND, T_{AMB} = T_{MIN} to T_{MAX}; refer to *Figure 1* test circuit. Note 2					
Supply Voltage Range	1.5		5.3	V	R_L = 500Ω
Start-Up Voltage		0.93		V	
Supply Current		10	18	mA	No Load
Max Output Current	200			mA	
Oscillator Input Current		±8		µA	
Oscillator Frequency	500	900	1250	kHz	
Output Resistance		5	7	Ω	I_L = 100mA, Note 3
Voltage Conversion Efficiency	99.0	99.6		%	No Load
Power Efficiency	78 65	84 79		%	I_L = 100mA I_L = 200mA
Doubler Circuit at High Frequency with 3.3µF Capacitors					
V+ = +5.0V, C1 = C2 = C3 = 3.3µF, FC = V+, LV = GND, T_{AMB} = T_{MIN} to T_{MAX}; refer to *Figure 2* test circuit. Note 2					
Supply Voltage Range	2.5		5.3	V	R_L = 1kΩ
Start-Up Voltage		1.5		V	
Supply Current		10	18	mA	No Load
Max Output Current	200			mA	
Oscillator Input Current		±8		µA	
Oscillator Frequency	500	900	1250	kHz	
Output Resistance		4.5	7	Ω	I_L = 100mA, Note 3
Voltage Conversion Efficiency	99.0	99.9		%	No Load
Power Efficiency	87 79	92 89		%	I_L = 100mA I_L = 200mA

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

NOTE 1: Specified output resistance is a combination of internal switch resistance and capacitor ESR.


NOTE 2: In the test circuit capacitors C1, C2 and C3 are 22µF, 0.05 maximum ESR, ceramic or 3.3µF, 0.05Ω maximum ESR, ceramic. Capacitors with higher ESR may reduce output voltage and efficiency. Refer to Capacitor Selection section.

NOTE 3: Specified output resistance is a combination of internal switch resistance and capacitor ESR. Refer to Optimizing Capacitor Selection.

 © Copyright 2004 Sipex Corporation

Optimizing Capacitor Selection

Refer to *Figure 1* for the total output resistance for various capacitance values and oscillator frequencies. The reservoir and charge pump capacitor values are equal. The capacitance values required to maintain comparable ripple and output resistance typically diminish proportionately as the pump frequency of the **SP6661** increases.



The product(or products)mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

Figure 1. Total Output Resistance for various capacitance values and oscillator frequencies.


 © Copyright 2004 Sipex Corporation

PIN DESCRIPTION

Pin Number	Pin Symbol	Description
1	FC	Frequency Control for the internal oscillator. FC = open, f_{osc} = 120kHz typical; FC = V+ f_{osc} = 900kHz typical.
2	CAP+	Connect to the positive terminal of the charge pump capacitor.
3	GND	(Voltage Inverter Circuit) Ground.
3	GND	(Positive Voltage Doubler Circuit) Positive supply voltage input.
4	CAP-	Connect to the negative terminal of the charge pump capacitor.
5	OUT	(Voltage Inverter Circuit) Negative voltage output pin.
5	OUT	(Positive Voltage Doubler Circuit) Ground pin for power supply.
6	LV	Low -voltage operation input pin in 660 circuits. In SP6661 circuits can be connected to GND, OUT or left open as desired with no effect.
7	OSC	Control pin for the oscillator. Internally connected to 15pF capacitor. An external capacitor can be added to slow the oscillator. Be careful to minimize stray capacitance. An external oscillator can be connected to overdrive the OSC pin.
8	V+	(Voltage Inverter Circuit) Positive voltage input pin for the power supply.
8	V+	(Positive Voltage Doubler Circuit) Positive voltage output.

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

 © Copyright 2004 Sipex Corporation




Pin #1 indentifier must be indicated within this shaded area (D/2 * E1/2)

8-PIN MSOP JEDEC MO-187 (AA) Variation	Dimensions in (mm)		
	MIN	NOM	MAX
A	-	-	1.10
A1	0	-	0.15
A2	0.75	0.85	0.95
b	0.22	-	0.38
c	0.08	-	0.23
D	3.00 BSC		
E	4.90 BSC		
E1	3.00 BSC		
e	0.65 BSC		
e1	1.95 BSC		
L	0.40	0.60	0.80
L1	0.95 REF		
L2	0.25 BSC		
N	-	8	-
R	0.07	-	-
R1	0.07	-	-
Ø	0°		8°
Ø1	0°	-	15°


The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)


8-PIN MSOP

 © Copyright 2004 Sipex Corporation




TOP VIEW






CONTACT AREA



VIEW C



SIDE VIEW

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

DIMENSIONS Minimum/Maximum (mm)	8 Pin NSOIC (JEDEC MS-012, AA - VARIATION)		
COMMON HEIGHT DIMENSION			
SYMBOL	MIN	NOM	MAX
A	1.35	-	1.75
A1	0.10	-	0.25
A2	1.25	-	1.65
b	0.31	-	0.51
c	0.17	-	0.25
D	4.90 BSC		
E	6.00 BSC		
E1	3.90 BSC		
e	1.27 BSC		
L	0.40	-	1.27
L1	1.04 REF		
L2	0.25 BSC		
Ø	0º	-	8º
Ø1	5º	-	15º

8 PIN NSOIC

 © Copyright 2004 Sipex Corporation

ORDERING INFORMATION

Part Number	Temperature Range	Package Type
SP6661EN	-40˚C to +85˚C	8-Pin NSOIC
SP6661EN/TR	-40˚C to +85˚C	8-Pin NSOIC
SP6661EU	-40˚C to +85˚C	8-Pin MSOP
SP6661EU/TR	-40˚C to +85˚C	8-Pin MSOP
SP6661EB		8-Pin MSOP Evaluation Board

Available in lead free packaging. To order add "-L" suffix to part number.

Example: SP6661EN/TR = standard; SP6661EN-L/TR = lead free

/TR = Tape and Reel

Pack quantity is 2,500 for MSOP & NSOIC.

The product (or products) mentioned in this data sheet are no longer being manufactured and may not be ordered (OBS)

ANALOG EXCELLENCE

Sipex Corporation

Headquarters:

233 Hillview Dr
Milpitas, CA 95035
TEL: (408) 934-7500
FAX: (408) 935-7600

Sipex Corporation reserves the right to make changes to any products described herein. Sipex does not assume any liability arising out of the application or use of any product or circuit described herein; neither does it convey any license under its patent rights nor the rights of others.